

Quad BTL Power Driver

AM5810

The AM5810 is a 4-channel BTL driver - 2 channels are able to use for stepping motor, and 1 channel is for reversible driver - designed to be used with ordinary electronic equipment (such as audio-visual equipment, office automation equipment, communications devices, electrical appliances, and electronic toys).

● Applications

CD players

● Features

- 1) A power saving mode is enabled by power-saver terminal.
- 2) Small surface mounting power package (HSOP-28)
- 3) Separating Vcc into Pre and Pow, can make better power efficiency
- 4) Thermal-shut-down circuit built in
- 5) Wide dynamic range <4.0V (Typ.) at PreVcc=12V, PowVcc=5V>
- 6) BTL driver: Input pins consist of (+) and (-), therefore various input types are available such as differential input.
- 7) Loading driver:
 - a. The output voltage is adjustable by output voltage control terminal. (Only "H" side voltage)
 - b. Brake circuit built in
 - c. Circuit protection diode built in

● Absolute Maximum Ratings


Parameter	Symbol	Limits	Unit
Supply voltage	PREVCC, POWVCC	13.5	V
Power dissipation	Pd	1.7*	W
Operating temperature	Topr	-40 ~ +85	°C
Storage temperature	Tstg	-55 ~ +150	°C

*On less than 3% (percentage occupied by copper foil), 70 x 70mm², t = 1.6mm, glass epoxy mounting. Reduce power by 13.5mV for each degree above 25°C.


- Guaranteed Operating Ranges

PREVCC	4.3 ~ 13.2V
POWVCC	4.3 ~ PREVCC

- Block Diagram




● Pin configuration



● Pin Description

PIN No	Pin Name	Description
1	FWD	Input for loading forward
2	REV	Input for loading reverse
3	LDCONT	Output control terminal for loading
4	PS	Control terminal for power saving mode
5	IN1	Input 1 of CH1
6	IN2	Input 2 of CH2
7	PREVCC	Pre and loading unit power supply input terminal
8	POWVCC12	Power unit power supply input terminal (CH1, CH2)
9	VOL (-)	Inverted output of loading
10	VOL (+)	Not inverted output of loading
11	VO2 (-)	Inverted output of CH2
12	VO2 (+)	Not inverted output of CH2
13	VO1 (-)	Inverted output of CH1
14	VO1 (+)	Not inverted output of CH1
15	VO4 (+)	Not inverted output of CH4
16	VO4 (-)	Inverted output of CH4
17	VO3 (+)	Not inverted output of CH3
18	VO3 (-)	Inverted output of CH3
19	GND	Substrate ground
20	POWVCC34	Power unit power supply input terminal (CH3, CH4)
21	MUTE	Input for mute control
22	OPOUT3	Output of CH3 OP-ANP
23	OPIN3 (-)	Inverting input of CH3 OP-ANP
24	OPIN3 (+)	Not inverting input of CH3 OP-ANP
25	OPOUT4	Output of CH4 OP-ANP
26	OPIN4 (-)	Inverting input of CH4 OP-ANP
27	OPIN4 (+)	Not inverting input of CH4 OP-ANP
28	BIAS	Input of Bias-Amplifier

● Application



- Electrical Characteristics (Unless otherwise specified, $T_a = 25^\circ C$, $PREVCC = 12V$, $POWVCC12/34 = 5V$, $BIAS = 1.65V$, $PS = 2V$, $RL = 8\Omega$)

Parameter	Symbol	Conditions	Limit			Unit
			Min	Typ	Max	
Quiescent Current	ICC	$RL = \infty$	-	22.9	34	mA
Power save on current	IPS	$PS = "L"$	-	1.65	2.8	mA
Power save on voltage	VPSON		-	-	0.5	V
Power save off voltage	VPSOFF		2.0	-	-	V

< BTL Driver >

Output offset voltage	VOO		-50	0	50	mV
Max. output voltage	VOM		3.6	4.0	-	V
Closed loop voltage gain	GVC		17.2	19.0	20.8	dB
Mute on voltage	VMTON		-	-	0.5	V
Mute off voltage	VMTOFF		1.5	-	-	V
Input current for mute pin	IMUTE	$VMUTE = 5V$	-	180	270	μA
Input current for Bias pin	IBIAS	$BVIAS = 2.5V$	-	75	120	μA

< OP-AMP (CH3,4) >

Common mode input voltage range	VICM		0.5	-	10.0	V
Input offset voltage	VOFOP		-6	0	6	mV
Input bias current	IBOP		-	-	300	nA
High level output voltage	VOHOP	$BIAS = 6V$	11.5	-	-	V
Low level output voltage	VOLOP	$BIAS = 6V$	-	-	0.5	V
Output sink current	ISIN		1	-	-	mA
Output source current	ISOU		1	-	-	mA
Slew rate	SROP	Input pulse 100KHz, 2Vp-p	-	1	-	V/ μs

< Loading Driver >

Output saturation voltage 1	VSAT1	Upper + Lower saturation, $IL = 200mA$	0.7	1.1	1.5	V
Output saturation voltage between F&R	Δ VSAT1	Output saturation voltage 1 between FWD and REV	-	-	0.1	V
Output saturation voltage 2	VSAT2	Upper + Lower saturation, $IL = 500mA$	1.0	1.55	2.2	V
Output adjustable gain on "H" side voltage	GVH	"H" side output for input (LDCNT)	7.4	9.2	11	dB

< Loading driver input logic >

Input high level voltage	VIHLD		1.5	-	VCC	V
Input low level voltage	VILLD		-0.3	-	0.5	V
Input high level current	IIHLD	$VFWD = VREV = 5V$	-	180	270	μA

※This product is not designed for protection against radioactive rays.

● Equivalent Circuit Of Terminals

Input of Bias Amplifier	Output of BTL Driver
Input of OP-AMP	Input for Mute - Loading Driver
Output of OP-AMP & Input of BLT Driver	Output of Loading Driver
Control Terminal for Power Saving Mode	Output Control Terminal for Loading