



SAW Components

Data Sheet B3817





SAW Components

B3817

Low-Loss Filter

208,0 MHz

Data Sheet


Ceramic package **QCC10B**

Features

- IF low-loss filter for W-CDMA base station
- Temperature stable
- Usable bandwidth 3,84 MHz
- Ceramic SMD package

Terminals


- Gold plated



Dimensions in mm, appr. weight 0,23 g

Pin configuration

- | | |
|------------|-----------------|
| 10 | Input |
| 9 | Input ground |
| 5, 4 | Balanced output |
| 1, 3, 6, 8 | Case ground |
| 2, 7 | To be grounded |



Type	Ordering code	Marking and Package according to	Packing according to
B3817	B39211-B3817-Z710	C61157-A7-A49	F61074-V8172-Z000

Electrostatic Sensitive Device (ESD)

Maximum ratings

Operable temperature range	T	-40 / +85	°C	
Storage temperature range	T_{stg}	-40 / +85	°C	
DC voltage	V_{DC}	0	V	
Source power	P_s	0	dBm	


SAW Components
B3817
Low-Loss Filter
208,0 MHz
Data Sheet
Characteristics

Operating temperature range: $T = 0 \dots 70 \text{ }^\circ\text{C}$
 Terminating source impedance: $Z_S = 50 \text{ } \Omega$ and matching network
 Terminating load impedance: $Z_L = 200 \text{ } \Omega$ and matching network

		min.	typ.	max.	
Nominal frequency	f_N	—	208,0	—	MHz
Minimum insertion attenuation (including matching network)	α_{\min} $f_N \pm 1,92 \text{ MHz}$	—	11,7	13,0	dB
Passband width	$\alpha_{\text{rel}} \leq 1 \text{ dB}$	$B_{1\text{dB}}$	—	4,2	— MHz
Amplitude ripple (p-p)	$\Delta\alpha$ $f_N \pm 1,92 \text{ MHz}$	—	0,7	1,0	dB
Phase ripple (p-p)	$\Delta\varphi$ $f_N \pm 1,92 \text{ MHz}$	—	7	10	$^\circ$
Phase ripple (rms)	$\Delta\varphi$ $f_N \pm 1,92 \text{ MHz}$	—	1,1	—	$^\circ$ rms
Absolute group delay mean value within $f_N \pm 1,92 \text{ MHz}$	τ_{mean}	790	795	800	ns
Relative attenuation (relative to α_{\min})	α_{rel}				
$f_N \pm 2,53 \text{ MHz} \dots f_N \pm 2,70 \text{ MHz}$		9	10	—	dB
$f_N \pm 2,70 \text{ MHz} \dots f_N \pm 2,75 \text{ MHz}$		15	20	—	dB
$f_N \pm 2,75 \text{ MHz} \dots f_N \pm 2,90 \text{ MHz}$		20	30	—	dB
$f_N \pm 2,90 \text{ MHz} \dots f_N \pm 3,30 \text{ MHz}$		25	30	—	dB
$f_N \pm 3,30 \text{ MHz} \dots f_N \pm 10 \text{ MHz}$		30	35	—	dB
$f_N \pm 10 \text{ MHz} \dots f_N \pm 28 \text{ MHz}$		40	50	—	dB
$f_N \pm 28 \text{ MHz} \dots f_N \pm 60 \text{ MHz}$		55	60	—	dB
Input IP3		40	—	—	dBm
Temperature coefficient of frequency¹⁾	TC_f	—	-0,036	—	ppm/K ²
Turnover temperature	T_0	—	25	—	$^\circ\text{C}$

¹⁾ Temperature dependance of f_c : $f_c(T_A) = f_c(T_0)(1 + TC_f(T_A - T_0)^2)$


SAW Components
B3817
Low-Loss Filter
208,0 MHz
Data Sheet
Characteristics

Operating temperature range: $T = -40 \dots 85 \text{ }^\circ\text{C}$
 Terminating source impedance: $Z_S = 50 \text{ } \Omega$ and matching network
 Terminating load impedance: $Z_L = 200 \text{ } \Omega$ and matching network


		min.	typ.	max.	
Nominal frequency	f_N	—	208,0	—	MHz
Minimum insertion attenuation (including matching network)	α_{\min} $f_N \pm 1,92 \text{ MHz}$	—	11,7	13,5	dB
Passband width	$\alpha_{\text{rel}} \leq 1 \text{ dB}$ $B_{1\text{dB}}$	—	4,2	—	MHz
Amplitude ripple (p-p)	$\Delta\alpha$ $f_N \pm 1,92 \text{ MHz}$	—	0,7	1,0	dB
Phase ripple (p-p)	$\Delta\varphi$ $f_N \pm 1,92 \text{ MHz}$	—	7	10	$^\circ$
Phase ripple (rms)	$\Delta\varphi$ $f_N \pm 1,92 \text{ MHz}$	—	1,1	—	$^\circ \text{ rms}$
Absolute group delay mean value within $f_N \pm 1,92 \text{ MHz}$	τ_{mean}	790	795	800	ns
Relative attenuation (relative to α_{\min})	α_{rel}				
$f_N \pm 2,53 \text{ MHz} \dots f_N \pm 2,70 \text{ MHz}$		8	10	—	dB
$f_N \pm 2,70 \text{ MHz} \dots f_N \pm 2,75 \text{ MHz}$		15	20	—	dB
$f_N \pm 2,75 \text{ MHz} \dots f_N \pm 2,90 \text{ MHz}$		20	30	—	dB
$f_N \pm 2,90 \text{ MHz} \dots f_N \pm 3,30 \text{ MHz}$		25	30	—	dB
$f_N \pm 3,30 \text{ MHz} \dots f_N \pm 10 \text{ MHz}$		30	35	—	dB
$f_N \pm 10 \text{ MHz} \dots f_N \pm 28 \text{ MHz}$		40	50	—	dB
$f_N \pm 28 \text{ MHz} \dots f_N \pm 60 \text{ MHz}$		55	60	—	dB
Input IP3		40	—	—	dBm
Temperature coefficient of frequency¹⁾	TC_f	—	- 0,036	—	ppm/K ²
Turnover temperature	T_0	—	25	—	$^\circ\text{C}$

1) Temperature dependance of f_c : $f_c(T_A) = f_c(T_0)(1 + TC_f(T_A - T_0)^2)$



Data Sheet

Matching network (element values depend on PCB layout):



$$C_{p1} = 39 \text{ pF}$$
$$L_{s2} = 68 \text{ nH}$$


$$L_{p3} = 390 \text{ nH}$$
$$L_{s4} = 47 \text{ nH}$$

$$C_{p5} = 22 \text{ pF}$$




Data Sheet

Transfer function



Transfer function (pass band)





SAW Components

B3817

Low-Loss Filter

208,0 MHz

Data Sheet

Published by EPCOS AG

Surface Acoustic Wave Components Division, SAW MC IS

P.O. Box 80 17 09, 81617 Munich, GERMANY

© EPCOS AG 2005. Reproduction, publication and dissemination of this brochure and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.

This brochure replaces the previous edition.

For questions on technology, prices and delivery please contact the Sales Offices of EPCOS AG or the international Representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our Sales Offices.