

FMM5057VF

7.1-8.5GHz Power Amplifier MMIC


FEATURES

- High Output Power: 34.0dBm(typ.)
- High Linear Gain: 26.0dB(typ.)
- Low VSWR
- Broad Band: 7.1 ~ 8.5GHz
- Impedance Matched $Z_{in}/Z_{out} = 50\Omega$
- Small Hermetic Metal-Ceramic Package(VF)

DESCRIPTION

The FMM5057VF is a MMIC amplifier that contains a four-stage amplifier, internally matched, for standard communications band in the 7.1 to 8.5GHz frequency range.

Fujitsu's stringent Quality Assurance Program assures the highest reliability and consistent performance.



ABSOLUTE MAXIMUM RATINGS (Case Temperature $T_c=25^\circ\text{C}$)

Item	Symbol	Rating	Unit
DC Input Voltage	V_{DD}	12	V
DC Input Voltage	V_{GG}	-7	V
Input Power	P_{in}	14	dBm
Storage Temperature	T_{stg}	-55 to +125	$^\circ\text{C}$

Recommended Operating Condition

Item	Symbol	Condition	Unit
DC Input Voltage at $T_c=25^\circ\text{C}$	V_{DD}	10	V
Input Power at $T_c=25^\circ\text{C}$	P_{in}	12	dBm
DC Input Current at $T_c=25^\circ\text{C}$	I_{DD}	≤ 1200	mA
Operating Case Temperature	T_c	-40 to +85	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS (Case Temperature $T_c=25^\circ\text{C}$)

Item	Symbol	Test Conditions	Limit			Unit
			Min.	Typ.	Max.	
Frequency Range	f		7.1 - 8.5			GHz
Output Power at 1dB G.C.P.	P_{1dB}	$V_{DD}=10V$ $V_{GG}=-5V$ $f=7.1$ to 8.5GHz	32.0	34.0	-	dBm
Power Gain at 1dB G.C.P.	G_{1dB}		23.0	26.0	-	dB
Gain Flatness	ΔG		-	2.4	4.0	dB
Input VSWR	$VSWR_i$		-	2 : 1	2.6 : 1	-
Output VSWR	$VSWR_o$		-	2 : 1	-	-
DC Input Current	I_{DD}	$V_{DD}=10V, V_{GG}=-5V$	-	1100	1200	mA
DC Input Current	I_{GG}		-	5.0	15.0	mA
Channel Temperature Rise	ΔT_{ch}		-	50	-	$^\circ\text{C}$

CASE STYLE: VF

G.C.P.: Gain Compression Point

Note: G_{1dB} is referenced to Linear Gain measured at $P_{in}=-3dBm$.

ESD	Class 0	~ 199 V
-----	---------	---------


Note : Based on EIAJ ED-4701 C-111A(C=100pF, R=1.5k Ω)

FMM5057VF

7.1-8.5GHz Power Amplifier MMIC


OUTPUT POWER vs. FREQUENCY

VDD=10V, VGG=-5V




OUTPUT POWER, POWER ADDED EFFICIENCY vs. INPUT POWER

VDD=10V, VGG=-5V




IMD vs. OUTPUT POWER

VDD=10V, VGG=-5V



VSWR vs. FREQUENCY


VDD=10V, VGG=-5V




FMM5057VF

7.1-8.5GHz Power Amplifier MMIC


DRAIN CURRENT vs OUTPUT POWER




AMPM vs OUTPUT POWER



OUTPUT POWER vs. DRAIN VOLTAGE




DRAIN CURRENT vs OUTPUT POWER




FMM5057VF

7.1-8.5GHz Power Amplifier MMIC


OUTPUT POWER , POWER ADDED EFFICIENCY vs. INPUT POWER




OUTPUT POWER , POWER ADDED EFFICIENCY vs. INPUT POWER



DRAIN CURRENT vs OUTPUT POWER




OUTPUT POWER vs. GATE VOLTAGE



FMM5057VF

7.1-8.5GHz Power Amplifier MMIC

■ S-PARAMETER




VDD=10.0V, VGG=-5.0V

Frequency [GHz]	S11		S21		S12		S22	
	MAG	ANG	MAG	ANG	MAG	ANG	MAG	ANG
6.9	0.22	-32.75	20.21	-147.13	0.0018	141.10	0.25	-1.17
7	0.19	-38.49	20.78	-171.17	0.0017	139.86	0.18	-7.55
7.1	0.16	-42.30	21.29	164.64	0.0017	144.62	0.11	-6.51
7.2	0.12	-42.44	21.74	140.28	0.0018	148.20	0.07	20.06
7.3	0.09	-32.59	22.04	115.51	0.0020	146.45	0.08	63.42
7.4	0.07	-2.59	22.24	90.84	0.0022	148.64	0.14	73.27
7.5	0.09	28.05	22.33	66.15	0.0025	143.94	0.20	68.70
7.6	0.13	38.99	22.35	41.55	0.0028	139.92	0.25	59.98
7.7	0.18	40.08	22.42	17.21	0.0031	134.35	0.29	49.76
7.8	0.23	36.58	22.37	-7.47	0.0033	127.55	0.33	38.34
7.9	0.28	31.41	22.44	-32.13	0.0036	121.48	0.36	26.63
8	0.33	24.61	22.42	-56.99	0.0038	116.50	0.38	14.30
8.1	0.36	16.99	22.41	-82.39	0.0040	105.95	0.38	1.81
8.2	0.39	8.76	22.35	-108.02	0.0042	97.60	0.37	-10.89
8.3	0.41	-0.24	22.15	-133.79	0.0044	89.83	0.36	-23.72
8.4	0.42	-9.50	21.99	-160.00	0.0044	81.16	0.33	-35.94
8.5	0.41	-19.29	21.71	173.43	0.0043	72.49	0.30	-47.13
8.6	0.40	-28.69	21.40	146.38	0.0041	63.50	0.26	-57.41

FMM5057VF

7.1-8.5GHz Power Amplifier MMIC

■ Recommended Bias Circuit and Internal Block Diagram



Note 1: The RC networks are recommended on the bias supply lines, close to the package, to prevent video oscillations which could damage the module.

Note 2: Bias point VDD can be connected at the input side or at the output. The two pins named VDD are internally connected.


PIN ASSIGNMENT

- 1 : VDD
- 2 : RF in
- 3 : VGG
- 4 : N.C.
- 5 : RF out
- 6 : VDD

FMM5057VF

7.1-8.5GHz Power Amplifier MMIC

■ Package Out Line



Unit : mm

FMM5057VF

7.1-8.5GHz Power Amplifier MMIC

For further information please contact :

FUJITSU COMPOUND SEMICONDUCTOR, INC.

2355 Zanker Rd.
San Jose, CA 95131-1138, U.S.A.
TEL: (408) 232-9500
FAX: (408) 428-9111
www.fcsi.fujitsu.com

FUJITSU QUANTUM DEVICES EUROPE LTD.

Network House
Norreys Drive
Maidenhead, Berkshire SL6 4FJ
TEL: +44 (0) 1628 504800
FAX: +44 (0) 1628 504888

FUJITSU QUANTUM DEVICES LIMITED

Business Development Division
11th Floor, Hachioji Daiichi-Seimei Bldg.
3-20-6 Myojin-cho
Hachioji-city, Tokyo 192-0046, Japan
TEL: +81-426-43-5885
FAX: +81-426-43-5582

FUJITSU QUANTUM DEVICES SINGAPORE PTE LTD.

Hong Kong Branch
Rm. 1101, Ocean Centre, 5 Canton Rd.
Tsim Sha Tsui, Kowloon, Hong Kong
TEL: +852-23770226
FAX: +852-23763269

CAUTION

Fujitsu Compound Semiconductor Products contain **gallium arsenide (GaAs)** which can be hazardous to the human body and the environment. For safety, observe the following procedures:

- Do not put these products into the mouth.
- Do not alter the form of this product into a gas, powder, or liquid through burning, crushing, or chemical processing as these by-products are dangerous to the human body if inhaled, ingested, or swallowed.
- Observe government laws and company regulations when discarding this product. This product must be discarded in accordance with methods specified by applicable hazardous waste procedures.

Fujitsu Limited reserves the right to change products and specifications without notice.
The information does not convey any license under rights of Fujitsu Limited or others.

© 2003 FUJITSU COMPOUND SEMICONDUCTOR, INC.
Printed in U.S.A. FCSI0202M200