

KEY FEATURES

- JAN/JANTX/JANTXV STANDARD PRODUCTS
- QUALIFIED PER MIL-PRF-19500/371
- LOW ON RESISTANCE
- FAST SWITCHING
- HIGH OFF ISOLATION
- HIGH POWER TRANSISTOR
- SECOND SOURCE FOR MICROSEMI
- DESIGNED FOR USE IN HIGH VOLTAGE INVERTERS, CONVERTERS, SWITCHING REGULATORS AND LINE OPERATED AMPLIFIERS



Part Number	Package	19500/	Emitter/Base Voltage	Collector Current
2N3902	TO-3	371	400V/700V	3.5A
2N5157	TO-3	371	500V/700V	3.5A


ABSOLUTE MAXIMUM RATINGS

Emitter-Base Voltage	2N3902 - 5V 2N5157 - 6V	Storage Temperature	-65 to 200°C
Base Current	2A	Operating Temperature	-65 to 200°C
Lead Temperature (1/16 from case, 10 sec)	300°C	Power Dissipation Derating	5W @ 25°C T _A 100W @ 75°C T _C 29mW/°C for T _A > 25°C 800mW/°C for T _C > 75°C

ORDERING GUIDE

JAN2N3902	JANTX2N3902	JANTXV2N3902
JAN2N5157	JANTX2N5157	JANTXV2N5157

TO-3 PACKAGE OUTLINE & PIN CONNECTIONS



Ltr	Dimensions			
	Inches		mm	
	Min.	Max.	Min.	Max.
CD		0.875		22.22
CH	0.250	0.328	6.35	8.33
HR	0.495	0.525	12.57	13.34
HR ₁	0.131	0.188	3.33	4.78
HT	0.060	0.135	1.52	3.43
LD	0.038	0.043	0.97	1.09
LL	0.312	0.500	7.92	12.70
L ₁		0.050		1.27
MHD	0.151	0.161	3.84	4.09
MHS	1.177	1.197	29.90	30.40
PS	0.420	0.440	10.67	11.18
PS ₁	0.205	0.225	5.21	5.72
S ₁	0.655	0.675	16.64	17.15

ELECTRICAL SPECIFICATIONS
 Typical @ 25°C unless otherwise noted

Parameter		Symbol	Min.	Max.	Unit
Collector-Emitter Sustaining Voltage $I_C = 100\text{mA}$	2N3902 2N5157	$V_{CE(SUS)}$	325 400		Vdc Vdc
Collector-Emitter Cutoff Current $V_{CE} = 700\text{Vdc}, V_{BE} = 1.5\text{Vdc}$		I_{CEX}		20	μA
Collector-Emitter Cutoff Current $V_{CE} = 400\text{Vdc}$ $V_{CE} = 500\text{Vdc}$	2N3902 2N5157	I_{CEO}		100 100	μA μA
Emitter-Base Cutoff Current $V_{EB} = 5\text{Vdc}$ $V_{EB} = 6\text{Vdc}$	2N3902 2N5157	I_{EB0}		200 200	μA μA
Forward-Current Transfer Ratio $I_C = 0.5\text{A}, V_{CE} = 5.0\text{Vdc}$ $I_C = 1.0\text{A}, V_{CE} = 5.0\text{Vdc}$ $I_C = 2.5\text{A}, V_{CE} = 5.0\text{Vdc}$ $I_C = 3.5\text{A}, V_{CE} = 5.0\text{Vdc}$		h_{FE}	25 30 10 5	90	
Thermal Resistance		$R_{\theta JC}$		1.25	c/w
Base-Emitter Saturated Voltage $I_B = 0.1\text{A}, I_C = 1.0\text{A}$ $I_B = 0.7\text{A}, I_C = 3.5\text{A}$		$V_{BE(sat)}$		1.5 2.0	Vdc Vdc
Collector-Emitter Saturated Voltage $I_B = 0.1\text{A}, I_C = 1.0\text{A}$ $I_B = 0.7\text{A}, I_C = 3.5\text{A}$		$V_{CE(sat)}$		0.8 2.5	Vdc Vdc
Small-Signal Short-Circuit Forward Current Transfer Ratio $I_C = 0.2\text{A}, V_{CE} = 10\text{Vdc}, f = 1.0\text{MHz}$		$ h_{fe} $	2.5	25	
Forward Current Transfer Ratio $I_C = 1\text{A}, V_{CE} = 5\text{Vdc}, T = -55^\circ\text{C}$		h_{fe}	10		
Output Capacitance $V_{CB} = 10\text{Vdc}, I_E = 0\text{A}, 100\text{kHz} \leq f \leq 1.0\text{MHz}$		C_{obo}		250	μF
Turn-On Time $V_{CC} = 125\text{Vdc}, I_C = 1.0\text{A}, I_{B1} = 0.1\text{A}$		t_{on}		0.8	μs
Turn-Off Time $V_{CC} = 125\text{Vdc}, I_C = 1.0\text{A}, I_{B1} = 0.1\text{A}, I_{B2} = 0.5\text{A}$		t_{off}		1.7	μs

SAFE OPERATING AREA
DC Tests (continuous) - $T_C = +25^\circ\text{C}; t^3 \leq 1.0\text{s}$ (See Figure 3 of MIL-PRF-19500/371)

Test 1 - $V_{CE} = 28.6\text{Vdc}, I_C = 3.5\text{A}$ | **Test 2** - $V_{CE} = 70\text{Vdc}, I_C = 1.43\text{A}$ | **Test 3 2N3902** - $V_{CE} = 325\text{Vdc}, I_C = 55\text{mA}$ | **Test 3 2N5157** - $V_{CE} = 400\text{Vdc}, I_C = 35\text{mA}$
Switching Tests, Load condition C (unclamped inductive load) - $T_C = 25^\circ\text{C};$ duty cycle = 10%; $R_S = 0.1\Omega$ (See Figure 4 of MIL-PRF-19500/371)

Test 1 - $t_P =$ approximately 3ms (vary to obtain I_C); $R_{BB1} = 20\Omega; V_{BB1} = 10\text{Vdc}; R_{BB2} = 3\text{k}\Omega; V_{BB2} = 1.5\text{Vdc}; V_{CC} = 50\text{Vdc}; I_C = 3.5\text{A}; L = 60\text{mH}; R = 3\Omega; R_L = 14\Omega.$
Test 2 - $t_P =$ approximately 3ms (vary to obtain I_C); $R_{BB1} = 100\Omega; V_{BB1} = 10\text{Vdc}; R_{BB2} = 3\text{k}\Omega; V_{BB2} = 1.5\text{Vdc}; I_C = 0.6\text{A}; V_{CC} = 50\text{Vdc}; L = 200\text{mH}; R = 8\Omega; R_L = 83\Omega.$
Switching Tests, Load condition (clamped inductive load) - $T_C = +25^\circ\text{C};$ duty cycle = 10%. (See Figure 5 of MIL-PRF-19500/371)

Test 1 - $t_P =$ approximately 30ms (vary to obtain I_C); $R_S = 0.1\Omega; R_{BB1} = 20\Omega; V_{BB1} = 10\text{Vdc}; R_{BB2} = 100\Omega; V_{BB2} = 1.5\text{Vdc}; V_{CC} = 50\text{Vdc}; I_C = 3.5\text{A}; L = 60\text{mH}; R = 3\Omega; R_L \geq 0\Omega.$

(A suitable clamping circuit or diode can be used.)

Clamp Voltage 2N3902 = 400 +0, -5 Vdc | **Clamp Voltage 2N5157** = 500 +0, -5 Vdc (Clamped voltage must be reached)

This document is believed to be correct at the time of publication and Solitron Devices accepts no responsibility for consequences from printing errors or inaccuracies. All specifications are subject to change without notice.