

LB1960M


Allowable Operating Ranges at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Recommended supply voltage	V _{CC} 1		3.6 to 17	V
Common mode input voltage range	V _{COM}		0.2 to HB	V

Electrical Characteristics at Ta = 25°C, VCC = 12V

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Circuit current	I _{CC}	In drive mode (CT = L)		2.3	4	mA
		In lockup protection mode (CT = H)		3	5	mA
CT capacitor charge current	I _{CT1}	V _{CT} = 0.2V	0.8	1.2	2.0	μA
Capacitor discharge current	I _{CT2}	V _{CT} = 8V	0.16	0.24	0.4	μA
Capacitor charge/discharge current ratio	R _{CT}	R _{CT} = I _{CT1} /I _{CT2}	4.0	5.0	7.0	–
CT charge voltage	V _{CT1}		6.8	7.2	7.6	V
CT discharge voltage	V _{CT2}		1.4	1.6	1.8	V
Output limiter withstand voltage	V _{OLM}	I _o = 1 mA	22.5	23.5	24.5	V
Output saturation voltage	V _{OSat}	I _o = 500 mA		1.0	1.3	V
Hall input sensitivity	V _{HN}	Including offset and hysteresis		6	12	mV
HB output H voltage	V _{HBH}	R _H = 350Ω	1.1	1.3	1.5	V
Thermal protection trigger temperature	T _{TSD}	Assured design target*	150	180	210	°C

* Assured design target: Target value, not measured individually




Truth Table

IN–	IN+	CT	OUT1	OUT2	Mode
H	L	L	L	H	Rotating
L	H		H	L	
–	–	H	off	off	Lock-up protection activated

LB1960M


Pin Assignment



Top view

Sample Application Circuit


5/12V power supply (3.8 to 18V)



Precautions

- If CT pin is connected to GND, the lockup protection and restart functions are disabled.
- In a circuit configuration as shown above, a power supply/GND reverse connection will cause a current to flow as follows: GND -> OUT -> coil -> power supply. The value of this current is limited by the coil resistance. If it is less than 500 mA, the IC will not be destroyed. If required, insert a diode between V_{CC} and the coil.

Block Diagram and Sample Application Circuit



- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of June, 1999. Specifications and information herein are subject to change without notice.