

MGF1402B

LOW NOISE GaAs FET

DESCRIPTION

The MGF1402B low-noise GaAs FET with an N-channel Schottky gate is designed for use in S to X band amplifiers and oscillators. The hermetically sealed metalceramic package assures minimum parasitic losses, and has a configuration suitable for microstrip circuits.

FEATURES

- Low noise figure $NF_{min} = 3.0\text{dB}$ (TYP.) @ $f = 12\text{GHz}$
- High associated gain $G_s = 8\text{dB}$ (TYP.) @ $f = 12\text{GHz}$
- High reliability and stability

APPLICATION


S to X band low-noise amplifiers and oscillators.

QUALITY GRADE

- IG, IGX, IGV

RECOMMENDED BIAS CONDITIONS

- $V_{DS} = 3\text{V}$
- $I_D = 10\text{mA}$
- Refer to Bias Procedure



ABSOLUTE MAXIMUM RATINGS ($T_a = 25^\circ\text{C}$)

Symbol	Parameter	Ratings	Unit
V_{GDO}	Gate to drain voltage	-6	V
V_{GSO}	Gate to source voltage	-6	V
I_D	Drain current	100	mA
P_T	Total power dissipation *1	360	mW
T_{Ch}	Channel temperature	175	$^\circ\text{C}$
T_{stg}	Storage temperature	-55 ~ +175	$^\circ\text{C}$






*1 : $T_c = 25^\circ\text{C}$

ELECTRICAL CHARACTERISTICS ($T_a = 25^\circ\text{C}$)

Symbol	Parameter	Test conditions	Limits			Unit
			Min	Typ	Max	
$V_{(BR)GDO}$	Gate to drain breakdown voltage	$I_G = -100\mu\text{A}$	-6	—	—	V
$V_{(BR)GSO}$	Gate to source breakdown voltage	$I_G = -100\mu\text{A}$	-6	—	—	V
I_{GSS}	Gate to source leakage current	$V_{GS} = -3\text{V}, V_{DS} = 0\text{V}$	—	—	10	μA
I_{DSS}	Saturated drain current	$V_{GS} = 0\text{V}, V_{DS} = 3\text{V}$	30	60	100	mA
$V_{GS(off)}$	Gate to source cut-off voltage	$V_{DS} = 3\text{V}, I_D = 100\mu\text{A}$	-0.3	—	-3.5	V
g_m	Transconductance	$V_{DS} = 3\text{V}, I_D = 10\text{mA}$	25	45	—	mS
G_s	Associated gain	$V_{DS} = 3\text{V}, I_D = 10\text{mA}, f = 12\text{GHz}$	5	8	—	dB
NF_{min}	Minimum noise figure	$V_{DS} = 3\text{V}, I_D = 10\text{mA}, f = 12\text{GHz}$	—	3.0	4.0	dB
$R_{th(ch-a)}$	Thermal resistance *1	ΔV_f method	—	—	416	$^\circ\text{C/W}$

*1: Channel to ambient

TYPICAL CHARACTERISTICS




LOW NOISE GaAs FET**NOISE PARAMETERS** ($V_{DS}=3V$, $I_D=10mA$)

Freq. (GHz)	Γ_{opt}		Rn (Ω)	NF min (dB)
	Magn.	Angle (deg.)		
4	0.649	61.5	28.0	0.96
8	0.437	138.1	32.0	1.85
12	0.414	-168.1	15.0	2.76


G_{lp} and P_{1dB} ($T_a=25^\circ C$, $V_D=3V$)

	f = 4GHz		f = 12GHz	
	$I_D=10mA$	$I_D=30mA$	$I_D=10mA$	$I_D=30mA$
G _{lp} (dB)	15.5	16.8	9.6	10.5
P _{1dB} (dBm)	12.6	14.5	10.5	12.7



S PARAMETERS ($T_a = 25^\circ\text{C}$, $V_{DS} = 3\text{V}$, $I_D = 10\text{mA}$)

Freq. (GHz)	S_{11}		S_{21}		S_{12}		S_{22}		K	MSG/MAG (dB)
	Mag.	Ang.	Mag.	Ang.	Mag.	Ang.	Mag.	Ang.		
0.5	0.995	-17.7	3.463	163.8	0.024	76.2	0.649	-13.6	0.067	21.6
1.0	0.974	-27.0	3.378	154.7	0.032	69.2	0.634	-20.8	0.178	20.2
1.5	0.954	-36.4	3.293	145.6	0.040	62.3	0.620	-28.1	0.255	19.2
2.0	0.933	-45.7	3.208	136.5	0.048	55.3	0.606	-35.3	0.315	18.3
2.5	0.913	-55.1	3.123	127.4	0.056	48.4	0.592	-42.6	0.367	17.5
3.0	0.892	-64.4	3.038	118.3	0.064	41.4	0.578	-49.8	0.412	16.8
3.5	0.872	-73.8	2.953	109.2	0.072	34.5	0.563	-57.1	0.454	16.1
4.0	0.851	-83.1	2.868	100.1	0.080	27.5	0.549	-64.3	0.494	15.5
4.5	0.827	-92.2	2.772	91.4	0.083	21.1	0.536	-71.6	0.554	15.2
5.0	0.802	-101.4	2.676	82.8	0.087	14.7	0.524	-78.9	0.617	14.9
5.5	0.778	-110.5	2.579	74.1	0.090	8.3	0.511	-86.2	0.680	14.5
6.0	0.753	-119.6	2.483	65.4	0.094	1.9	0.498	-93.5	0.747	14.2
6.5	0.736	-126.4	2.401	58.2	0.095	-3.1	0.495	-99.6	0.803	14.0
7.0	0.719	-133.2	2.319	51.1	0.095	-8.0	0.493	-105.8	0.862	13.9
7.5	0.702	-140.0	2.238	43.9	0.096	-13.0	0.491	-111.9	0.926	13.7
8.0	0.685	-146.8	2.156	36.7	0.097	-17.9	0.488	-118.0	0.993	13.5
8.5	0.669	-153.3	2.109	29.8	0.097	-22.5	0.488	-123.1	1.053	12.0
9.0	0.652	-159.8	2.061	23.0	0.098	-27.2	0.487	-128.3	1.115	11.2
9.5	0.636	-166.2	2.014	16.1	0.098	-31.8	0.487	-133.4	1.179	10.6
10.0	0.619	-172.7	1.967	9.2	0.098	-36.4	0.487	-138.5	1.244	10.1
10.5	0.603	-179.9	1.931	2.0	0.098	-41.1	0.484	-143.9	1.313	9.6
11.0	0.586	172.9	1.895	-5.3	0.098	-45.8	0.481	-149.2	1.384	9.2
11.5	0.569	165.7	1.858	-12.6	0.097	-50.4	0.478	-154.6	1.458	8.8
12.0	0.553	158.5	1.822	-19.8	0.097	-55.1	0.475	-159.9	1.535	8.4



S PARAMETERS (Ta = 25°C, V_{DS} = 3V, I_D = 30mA)

Freq. (GHz)	S ₁₁		S ₂₁		S ₁₂		S ₂₂		K	MSG/MAG (dB)
	Mag.	Ang.	Mag.	Ang.	Mag.	Ang.	Mag.	Ang.		
0.5	0.997	-22.7	5.280	159.8	0.023	73.1	0.592	-16.3	0.055	23.7
1.0	0.966	-33.5	5.084	150.2	0.028	66.5	0.576	-23.2	0.198	22.6
1.5	0.934	-44.2	4.889	140.7	0.034	59.8	0.559	-30.2	0.307	21.6
2.0	0.902	-54.9	4.694	131.1	0.039	53.1	0.543	-37.1	0.398	20.8
2.5	0.870	-65.6	4.499	121.6	0.045	46.4	0.526	-44.1	0.477	20.0
3.0	0.838	-76.4	4.303	112.0	0.050	39.8	0.510	-51.0	0.550	19.3
3.5	0.807	-87.1	4.108	102.5	0.056	33.1	0.493	-58.0	0.620	18.7
4.0	0.775	-97.8	3.913	92.9	0.061	26.4	0.477	-64.9	0.689	18.1
4.5	0.748	-107.6	3.730	84.3	0.063	21.4	0.467	-71.6	0.764	17.7
5.0	0.720	-117.5	3.546	75.7	0.065	16.3	0.457	-78.3	0.846	17.4
5.5	0.693	-127.3	3.362	67.1	0.066	11.3	0.447	-85.0	0.935	17.1
6.0	0.666	-137.1	3.179	58.5	0.068	6.2	0.437	-91.7	1.033	15.6
6.5	0.648	-144.5	3.050	51.5	0.068	2.7	0.437	-96.8	1.108	14.5
7.0	0.631	-152.0	2.922	44.6	0.069	-0.8	0.437	-101.9	1.189	13.7
7.5	0.613	-159.4	2.793	37.6	0.069	-4.2	0.438	-106.9	1.278	12.9
8.0	0.595	-166.8	2.665	30.6	0.069	-7.7	0.438	-112.0	1.374	12.2
8.5	0.579	-174.3	2.586	23.7	0.069	-11.0	0.440	-116.7	1.451	11.8
9.0	0.563	178.2	2.507	16.9	0.069	-14.3	0.441	-121.4	1.531	11.3
9.5	0.547	170.7	2.427	10.0	0.069	-17.6	0.443	-126.0	1.617	10.9
10.0	0.531	163.2	2.348	3.1	0.069	-20.9	0.445	-130.7	1.707	10.4
10.5	0.516	155.9	2.293	-4.0	0.070	-24.6	0.445	-135.1	1.770	10.1
11.0	0.502	148.5	2.238	-11.0	0.070	-28.2	0.444	-139.5	1.834	9.7
11.5	0.487	141.2	2.183	-18.1	0.071	-31.9	0.444	-143.8	1.900	9.4
12.0	0.472	133.8	2.128	-25.1	0.072	-35.5	0.444	-148.2	1.968	9.1

Requests Regarding Safety Designs

Mitsubishi Electric constantly strives to raise the level of its quality and reliability. Despite these concerted efforts, however, there will be occasions when our semiconductor products suffer breakdowns, malfunctions or other problems. In view of this reality, it is requested that every feasible precaution be taken in the pursuit of redundancy design, malfunction prevention design and other safety-related designs, to prevent breakdowns or malfunctions in our products from resulting in accidents involving people, fires, social losses or other problems, thereby upholding the highest levels of safety in the products when in use by customers.

Matters of Importance when Using these Materials

1. These materials are designed as reference materials to ensure that all customers purchase Mitsubishi Electric semiconductors best suited to their specific use applications. Please be aware, however, that the technical information contained in these materials does not comprise consent for the execution or use of intellectual property rights or other rights owned by Mitsubishi Electric Corporation.
2. Mitsubishi Electric does not assume responsibility for damages resulting from the use of product data, graphs, charts, programs, algorithms or other applied circuit examples described in these materials, or for the infringement of the rights of third-party owners resulting from such use.
3. The data, graphs, charts, programs, algorithms and all other information described in these materials were current at the issue of these materials, with Mitsubishi Electric reserving the right to make any necessary updates or changes in the products or specifications in these materials without prior notice. Before purchasing Mitsubishi Electric semiconductor products, therefore, please obtain the latest available information from Mitsubishi Electric directly or an authorized dealer.
4. Every possible effort has been made to ensure that the information described in these materials is fully accurate. However, Mitsubishi Electric assumes no responsibility for damages resulting from inaccuracies occurring within these materials.
5. When using the product data, technical contents indicated on the graphs, charts, programs or algorithms described in these materials, assessments should not be limited to only the technical contents, programs and algorithm units. Rather, it is requested that ample evaluations be made of each individual system as a whole, with the customer assuming full responsibility for decisions on the propriety of application. Mitsubishi Electric does not accept responsibility for the propriety of application.
6. The products described in these materials, with the exception of special mention concerning use and reliability, have been designed and manufactured with the purpose of use in general electronic machinery. Accordingly these products have not been designed and manufactured with the purpose of application in machinery or systems that will be used under conditions that can affect human life, or in machinery or systems used in social infrastructure that demand a particularly high degree of reliability. When considering the use of the products described in these materials in transportation machinery (automobiles, trains, vessels), for objectives related to medical treatment, aerospace, nuclear power control, submarine repeaters or systems or other specialized applications, please consult with Mitsubishi Electric directly or an authorized dealer.
7. When considering use of products for purposes other than the specific applications described in these materials, please inquire at Mitsubishi Electric or an authorized dealer.
8. The prior consent of Mitsubishi Electric in writing is required for any reprinting or reproduction of these materials.
9. Please direct any inquiries regarding further details of these materials, or any other comments or matters of attention, to Mitsubishi Electric or an authorized dealer.