

ML674000**32-bit General-purpose, ARM-based Microcontroller****GENERAL DESCRIPTION**

Oki's ML674000 standard microcontroller (MCU) is a member of an extensive and growing family of ARM[®] architecture 32-bit MCUs for general-purpose applications that require 32-bit CPU performance and low cost afforded by MCU integrated features.

ML674000 MCU provides a host of useful peripherals such as 8KB of on-board SRAM, timers, watchdog timer, pulse-width modulators, AD converter, UART's, GPIO connectivity capability, and external memory controller. These integrated features make it ideal for embedded applications where low costs and low power consumption are key.

Oki's ML674K series MCUs are capable of executing both the 32-bit ARM instruction set for high-performance applications as well as the 16-bit Thumb[®] instruction set for power-efficient applications. With an ARM7TDMI[®] core operating at 33 MHz maximum frequency, ARM Thumb[™] capabilities, and robust feature sets, the ML674K series MCUs are suitable for an array of applications including high performance industrial controllers and instrumentation, telecom, PC peripherals, security/surveillance, test equipment, and a variety of consumer electronics devices.

The ARM7TDMI[®] Advantage

Oki's ML67 Family of low-cost ARM-based MCUs offers system designers a bridge from 8- and 16-bit proprietary MCU architectures to ARM's higher-performance, affordable, widely-accepted industry standard architecture and its industry-wide support infrastructure. The ARM industry infrastructure offers system developers many advantages including software compatibility, many ready-to-use software applications, and numerous choices among hardware and software development tools. These ARM-based advantages allow Oki's customers to better leverage engineering resources, lower development costs, minimize project risks, and reduce their product time to market. In addition, migration of a design with an Oki standard MCU to an Oki custom solution is easily facilitated with its award-winning μ PLAT[™] product development architecture.

FEATURES

- CPU
 - 32-bit RISC CPU (ARM7TDMI)
 - 32-bit instructions (ARM Instructions) and 16-bit instructions (Thumb Instructions) mixed
 - General purpose registers : 31 x 32 bits
 - Built-in Barrel shifter and multiplier (32 bit x 8 bit, Modified Booth's Algorithm)
 - Little endian
 - Built-in debug function
- Internal memory
 - RAM 8KB (32-bit access)
- External memory controller
 - ROM (FLASH): 16 Mbytes
 - SRAM: 16 Mbytes
 - DRAM: 64 Mbytes (SDRAM and EDO-DRAM support)
 - External IO devices: 16 Mbytes x 2 banks (with wait control by external signal)



ARM, ARM7TDMI, Multi-ICE and AMBA are registered trademarks of ARM Ltd., UK.

μ PLAT is Oki's trademark.

The contents of this data sheet are subject to change for modification without notice.

- Interrupt controller
 - 24 sources: 19 internals and 5 externals (IRQ: 4, FIQ: 1)
- DMA controller
 - 2 channels: Dual address mode, cycle steal and burst transfer mode
- Timer
 - 1 channel: 16-bit auto reload for operating system
 - 6 channels: 16-bit auto reload for application
 - 1 channel: 16 bit watchdog timer
- Serial interface
 - 1 channel: UART
 - 1 channel: UART with 16-byte FIFO
- Parallel I/O Port
 - 2 ports x 16 bits (bitwise input/output settings)
- PWM
 - 2 channels x 16 bits
- Analog-to-Digital Converter
 - 8 channels x 10 bits
- Power down mechanism
 - Standby (all clock stop) and Halt (clock stop by each function block)
 - Clock gear (selectable 1/1, 1/2, 1/4, 1/8, 1/16 input clock frequency)
- JTAG interface
 - Connectable to JTAG ICE (e.g. ARM MuliICE)
- Power supply voltage
 - Core section: 2.25 V to 2.75 V
 - IO section: 3.0 V to 3.6 V
- Operating frequency
 - 33 MHz (Max.)
- Operating temperature (ambient temperature)
 - 40°C to +85°C
- Package
 - 128-pin plastic TQFP (P-TQFP128-1414-0.40-K)
 - 144-pin plastic LFBGA (P-LFBGA144-1111-0.80)

PIN CONFIGURATION (TOP VIEW)

(Secondary function)	(Primary function)	(Primary function)	(Secondary function)	(Primary function)	(Secondary function)
XWR	PIOA[15]	97			
	XOE_N	98			
	XWE_N	99			
	GND_IO	100			
	XBWE_N[0]	101			
	XBWE_N[1]	102			
	XROMCS_N	103			
	XRAMCS_N	104			
	XIOCS_N[0]	105			
	XIOCS_N[1]	106			
	GND_CORE	107			
	VDD_CORE	108			
DREQ0	PIOB[0]	109			
DREQCLR0	PIOB[1]	110			
	VDD_IO	111			
DREQ1	PIOB[2]	112			
DREQCLR1	PIOB[3]	113			
TCOUT0	PIOB[4]	114			
TCOUT1	PIOB[5]	115			
	GND_IO	116			
PWMOUT0	PIOB[6]	117			
PWMOUT1	PIOB[7]	118			
	XBS_N[0]	119			
	XBS_N[1]	120			
XWAIT	PIOB[8]	121			
XCAS_N	PIOB[9]	122			
XRAS_N	PIOB[10]	123			
XSDCLK	PIOB[11]	124			
XSDCS_N	PIOB[12]	125			
XSDCKE	PIOB[13]	126			
	VDD_IO	127			
	GND_IO	128			
		1			
		2			
		3			
		4			
		5			
		6			
		7			
		8			
		9			
		10			
		11			
		12			
		13			
		14			
		15			
		16			
		17			
		18			
		19			
		20			
		21			
		22			
		23			
		24			
		25			
		26			
		27			
		28			
		29			
		30			
		31			
		32			
		33			
		34			
		35			
		36			
		37			
		38			
		39			
		40			
		41			
		42			
		43			
		44			
		45			
		46			
		47			
		48			
		49			
		50			
		51			
		52			
		53			
		54			
		55			
		56			
		57			
		58			
		59			
		60			
		61			
		62			
		63			
		64			
		65			
		66			
		67			
		68			
		69			
		70			
		71			
		72			
		73			
		74			
		75			
		76			
		77			
		78			
		79			
		80			
		81			
		82			
		83			
		84			
		85			
		86			
		87			
		88			
		89			
		90			
		91			
		92			
		93			
		94			
		95			
		96			
		97			
		98			
		99			
		100			
		101			
		102			
		103			
		104			
		105			
		106			
		107			
		108			
		109			
		110			
		111			
		112			
		113			
		114			
		115			
		116			
		117			
		118			
		119			
		120			
		121			
		122			
		123			
		124			
		125			
		126			
		127			
		128			
		129			
		130			
		131			
		132			
		133			
		134			
		135			
		136			
		137			
		138			
		139			
		140			
		141			
		142			
		143			
		144			
		145			
		146			
		147			
		148			
		149			
		150			
		151			
		152			
		153			
		154			
		155			
		156			
		157			
		158			
		159			
		160			
		161			
		162			
		163			
		164			
		165			
		166			
		167			
		168			
		169			
		170			
		171			
		172			
		173			
		174			
		175			
		176			
		177			
		178			
		179			
		180			
		181			
		182			
		183			
		184			
		185			
		186			
		187			
		188			
		189			
		190			
		191			
		192			
		193			
		194			
		195			
		196			
		197			
		198			
		199			
		200			
		201			
		202			
		203			
		204			
		205			
		206			
		207			
		208			
		209			
		210			
		211			
		212			
		213			
		214			
		215			
		216			
		217			
		218			
		219			
		220			
		221			
		222			
		223			
		224			
		225			
		226			
		227			
		228			
		229			
		230			
		231			
		232			
		233			
		234			
		235			
		236			
		237			
		238			
		239			
		240			
		241			
		242			
		243			
		244			
		245			
		246			
		247			
		248			
		249			
		250			
		251			
		252			
		253			
		254			
		255			
		256			
		257			
		258			
		259			
		260			
		261			
		262			
		263			
		264			
		265			
		266			
		267			
		268			
		269			
		270			
		271			
		272			
		273			
		274			
		275			
		276			
		277			
		278			
		279			
		280			
		281			
		282			
		283			
		284			
		285			
		286			
		287			
		288			
		289			
		290			
		291			
		292			
		293			
		294			
		295			
		296			
		297			
		298			
		299			
		300			
		301			
		302			
		303			
		304			
		305			
		306			
		307			
		308			
		309			
		310			
		311			
		312			
		313			
		314			
		315			
		316			
		317			
		318			
		319			
		320			
		321			
		322			
		323			
		324			
		325			
		326			
		327			
		328			
		329			
		330			
		331			
		332			

	A	B	C	D	E	F	G	H	J	K	L	M	N	
13	NC	NC	NC	PIOA[12]/ XA[21]	XA[18]	XA[16]	GND_ CORE	XA[8]	XA[5]	XA[2]	GND_IO	XD[15]	NC	13
12	PIOA[15]/ XWR	PIOA[14]/ XA[23]	VDD_IO	GND_IO	XA[15]	XA[14]	XA[10]	GND_IO	XA[7]	XA[4]	XA[1]	NC	XD[14]	12
11	XOE_N	GND_IO	NC	PIOA[11]/ XA[20]	PIOA[10]/ XA[19]	VDD_ CORE	XA[12]	XA[9]	XA[3]	XA[0]	NC	VDD_IO	XD[13]	11
10	XBWE_ N[0]	XROM CS_N	XWE_N	PIOA[13]/ XA[22]	XA[17]	XA[13]	XA[11]	VDD_IO	XA[6]	XD[12]	XD[10]	GND_IO	XD[11]	10
9	XRAM CS_N	XIOCS_ N[1]	XBWE_ N[1]	XIOCS_ N[0]						XD[7]	XD[9]	XD[5]	XD[8]	9
8	GND_ CORE	VDD_ CORE	PIOB[1]/ DREQCLR 0	PIOB[0]/ DREQ0						XD[3]	XD[2]	XD[4]	XD[6]	8
7	PIOB[4]/ TCOUT0	VDD_IO	PIOB[3]/ DREQCLR 1	PIOB[2]/ DREQ1						XD[0]	XD[1]	NC	NC	7
6	XBS_N[0]	PIOB[6]/ PWMOUT0	PIOB[5]/ TCOUT1	GND_IO						NC	VDD_ CORE	OSC1_N	OSC0	6
5	PIOB[9]/ XCAS_N	PIOB[7]/ PWMOUT 1	PIOB[10]/ XCRAS_N	XBS_N[1]						GND_IO	EXINT3	GND_ CORE	RESET_N	5
4	PIOB[12]/ XSDCS_N	PIOB[8]/ XWAIT	PIOB[11]/ XSCLK	VDD_IO	TCK	PIOA[2]/ CTS	PIOA[5]/ DTR	VDD_ CORE	AIN[0]	AIN[7]	EXINT0	EFIQ_N	EXINT2	4
3	NC	PIOB[13]/ XSCKE	NC	DBGQR	TDO	PIOA[3]/ DSR	PIOA[6]/ RTS	GND_ CORE	AIN[3]	AIN[4]	PIOA[8]/ STXD	EXINT1	PIOA[9]/ SRXD	3
2	NC	GND_IO	DBGACK	nTRST	TBE	PIOA[1]/ SOUT	PIOA[4]/ DCD	NC	AVDD	AIN[1]	AIN[6]	NC	MODE[2]	2
1	NC	PIOB[14]/ XDQM[1]/ XCAS_N[1]	PIOB[15]/ XDQM[0]/ XCAS_N[0]	TDI	TMS	PIOA[0]/ SIN	PIOA[7]/ RI	VREF	AIN[2]	AIN[5]	AGND	MODE[0]	MODE[1]	1
	A	B	C	D	E	F	G	H	J	K	L	M	N	

Note: Don't connect NC pins with others.

144-Pin Plastic LFBGA

LIST OF PINS

Pin Number		Primary Function			Secondary Function		
TQFP	LFBGA	Pin Name	I/O	Function	Pin Name	I/O	Function
1	B1	PIOB[14]	I/O	General-purpose port (with interrupt function)	XDQM[1]/ XCAS_N[1]	O	I/O mask/CAS (MSB)
2	C1	PIOB[15]	I/O	General-purpose port (with interrupt function)	XDQM[0]/ XCAS_N[0]	O	I/O mask/CAS (LSB)
3	D3	DBGRQ	I	Debugging input signal	—	—	
4	C2	DBGACK	O	Debugging output signal	—	—	
5	D1	TDI	I	JTAG data input	—	—	
6	E3	TDO	O	JTAG data output	—	—	
7	D2	nTRST	I	JTAG reset	—	—	
8	E1	TMS	I	JTAG mode select	—	—	
9	E4	TCK	I	JTAG clock	—	—	
10	E2	TBE	I	Test input signal	—	—	
11	F1	PIOA[0]	I/O	General-purpose port (with interrupt function)	SIN	I	UART Serial Data In
12	F2	PIOA[1]	I/O	General-purpose port (with interrupt function)	SOUT	O	UART Serial Data Out
13	F4	PIOA[2]	I/O	General-purpose port (with interrupt function)	CTS	I	UART Clear To Send
14	F3	PIOA[3]	I/O	General-purpose port (with interrupt function)	DSR	I	UART Set Ready
15	G2	PIOA[4]	I/O	General-purpose port (with interrupt function)	DCD	I	UART Carrier Detect
16	G4	PIOA[5]	I/O	General-purpose port (with interrupt function)	DTR	O	UART Data Terminal Ready
17	G3	PIOA[6]	I/O	General-purpose port (with interrupt function)	RTS	O	UART Request To Send
18	G1	PIOA[7]	I/O	General-purpose port (with interrupt function)	RI	I	UART Ring Indicator
19	H3	GND_CORE	GND	Core ground	—	—	
20	H4	VDD_CORE	VDD	Core power supply	—	—	
21	J2	AVDD	VDD	Analog-to-digital converter power supply	—	—	
22	H1	VREF	I	Analog-to-digital converter reference voltage	—	—	
23	J4	AIN[0]	I	Analog-to-digital converter analog input	—	—	
24	K2	AIN[1]	I	Analog-to-digital converter analog input	—	—	
25	J1	AIN[2]	I	Analog-to-digital converter analog input	—	—	
26	J3	AIN[3]	I	Analog-to-digital converter analog input	—	—	
27	K3	AIN[4]	I	Analog-to-digital converter analog input	—	—	
28	K1	AIN[5]	I	Analog-to-digital converter analog input	—	—	
29	L2	AIN[6]	I	Analog-to-digital converter analog input	—	—	
30	K4	AIN[7]	I	Analog-to-digital converter analog input	—	—	
31	L1	AGND	GND	GND for A/D converter	—	—	
32	M1	MODE[0]	I	Mode setting	—	—	
33	N1	MODE[1]	I	Mode setting	—	—	
34	N2	MODE[2]	I	Mode setting	—	—	
35	L3	PIOA[8]	I/O	General-purpose port (with interrupt function)	STXD	O	SIO transmit data output
36	N3	PIOA[9]	I/O	General-purpose port (with interrupt function)	SRXD	I	SIO receive data input
37	L4	EXINT0	I	Interrupt input	—	—	
38	M3	EXINT1	I	Interrupt input	—	—	
39	N4	EXINT2	I	Interrupt input	—	—	

Pin Number		Primary Function			Secondary Function		
TQFP	LFBGA	Pin Name	I/O	Function	Pin Name	I/O	Function
40	L5	EXINT3	I	Interrupt input	—	—	
41	M4	EFIQ_N	I	FIQ input	—	—	
42	N5	RESET_N	I	Reset input	—	—	
43	K5	GND_IO	GND	I/O ground	—	—	
44	M5	GND_CORE	GND	Core ground	—	—	
45	N6	OSC0	I	Oscillator input	—	—	
46	M6	OSC1_N	O	Oscillator output	—	—	
47	L6	VDD_CORE	VDD	Core power supply	—	—	
48	K7	XD[0]	I/O	External data bus	—	—	
49	L7	XD[1]	I/O	External data bus	—	—	
50	L8	XD[2]	I/O	External data bus	—	—	
51	K8	XD[3]	I/O	External data bus	—	—	
52	M8	XD[4]	I/O	External data bus	—	—	
53	M9	XD[5]	I/O	External data bus	—	—	
54	N8	XD[6]	I/O	External data bus	—	—	
55	K9	XD[7]	I/O	External data bus	—	—	
56	M10	GND_IO	GND	I/O ground	—	—	
57	N9	XD[8]	I/O	External data bus	—	—	
58	L9	XD[9]	I/O	External data bus	—	—	
59	L10	XD[10]	I/O	External data bus	—	—	
60	N10	XD[11]	I/O	External data bus	—	—	
61	M11	VDD_IO	VDD	I/O power supply	—	—	
62	K10	XD[12]	I/O	External data bus	—	—	
63	N11	XD[13]	I/O	External data bus	—	—	
64	N12	XD[14]	I/O	External data bus	—	—	
65	M13	XD[15]	I/O	External data bus	—	—	
66	L13	GND_IO	GND	I/O ground	—	—	
67	K11	XA[0]	O	External address output	—	—	
68	L12	XA[1]	O	External address output	—	—	
69	K13	XA[2]	O	External address output	—	—	
70	J11	XA[3]	O	External address output	—	—	
71	K12	XA[4]	O	External address output	—	—	
72	J13	XA[5]	O	External address output	—	—	
73	J10	XA[6]	O	External address output	—	—	
74	J12	XA[7]	O	External address output	—	—	
75	H13	XA[8]	O	External address output	—	—	
76	H12	GND_IO	GND	I/O ground	—	—	
77	H10	VDD_IO	VDD	I/O power supply	—	—	
78	H11	XA[9]	O	External address output	—	—	
79	G12	XA[10]	O	External address output	—	—	
80	G10	XA[11]	O	External address output	—	—	
81	G11	XA[12]	O	External address output	—	—	

Pin Number		Primary Function			Secondary Function		
TQFP	LFBGA	Pin Name	I/O	Function	Pin Name	I/O	Function
82	G13	GND_CORE	GND	Core ground	—	—	
83	F11	VDD_CORE	VDD	Core power supply	—	—	
84	F10	XA[13]	O	External address output	—	—	
85	F12	XA[14]	O	External address output	—	—	
86	E12	XA[15]	O	External address output	—	—	
87	F13	XA[16]	O	External address output	—	—	
88	E10	XA[17]	O	External address output	—	—	
89	D12	GND_IO	GND	I/O ground	—	—	
90	E13	XA[18]	O	External address output	—	—	
91	E11	PIOA[10]	I/O	General-purpose port (with interrupt function)	XA[19]	O	External address output
92	D11	PIOA[11]	I/O	General-purpose port (with interrupt function)	XA[20]	O	External address output
93	D13	PIOA[12]	I/O	General-purpose port (with interrupt function)	XA[21]	O	External address output
94	C12	VDD_IO	VDD	I/O power supply	—	—	
95	D10	PIOA[13]	I/O	General-purpose port (with interrupt function)	XA[22]	O	External address output
96	B12	PIOA[14]	I/O	General-purpose port (with interrupt function)	XA[23]	O	External address output
97	A12	PIOA[15]	I/O	General-purpose port (with interrupt function)	XWR	O	External bus data transfer direction
98	A11	XOE_N	O	Output enable (except SDRAM)	—	—	
99	C10	XWE_N	O	Write enable	—	—	
100	B11	GND_IO	GND	I/O ground	—	—	
101	A10	XBWE_N[0]	O	Write enable (LSB)	—	—	
102	C9	XBWE_N[1]	O	Write enable (MSB)	—	—	
103	B10	XROMCS_N	O	External ROM chip select	—	—	
104	A9	XRAMCS_N	O	External RAM chip select	—	—	
105	D9	XIOCS_N[0]	O	I/O bank 0 chip select	—	—	
106	B9	XIOCS_N[1]	O	I/O bank 1 chip select	—	—	
107	A8	GND_CORE	GND	Core ground	—	—	
108	B8	VDD_CORE	VDD	Core power supply	—	—	
109	D8	PIOB[0]	I/O	General-purpose port (with interrupt function)	DREQ0	I	DMA request signal (Ch 0)
110	C8	PIOB[1]	I/O	General-purpose port (with interrupt function)	DREQCLR0	O	DREQ clear signal (Ch 0)
111	B7	VDD_IO	VDD	I/O power supply	—	—	
112	D7	PIOB[2]	I/O	General-purpose port (with interrupt function)	DREQ1	I	DMA request signal (Ch 1)
113	C7	PIOB[3]	I/O	General-purpose port (with interrupt function)	DREQCLR1	O	DREQ clear signal (Ch 1)
114	A7	PIOB[4]	I/O	General-purpose port (with interrupt function)	TCOUT0	O	DMA Termination Signal (CH 0)
115	C6	PIOB[5]	I/O	General-purpose port (with interrupt function)	TCOUT1	O	DMA Termination Signal (CH 1)
116	D6	GND_IO	GND	I/O ground	—	—	
117	B6	PIOB[6]	I/O	General-purpose port (with interrupt function)	PWMOUT0	O	PWM output (Ch 0)
118	B5	PIOB[7]	I/O	General-purpose port (with interrupt function)	PWMOUT1	O	PWM output (Ch 1)
119	A6	XBS_N[0]	O	External bus byte select (LSB)	—	—	
120	D5	XBS_N[1]	O	External bus byte select (MSB)	—	—	
121	B4	PIOB[8]	I/O	General-purpose port (with interrupt function)	XWAIT	I	WAIT input for IO bank 0
122	A5	PIOB[9]	I/O	General-purpose port (with interrupt function)	XCAS_N	O	Column address strobe (SDRAM)
123	C5	PIOB[10]	I/O	General-purpose port (with interrupt function)	XRAS_N	O	Row address strobe (SDRAM/EDO)

Pin Number		Primary Function			Secondary Function		
TQFP	LFBGA	Pin Name	I/O	Function	Pin Name	I/O	Function
124	C4	PIOB[11]	I/O	General-purpose port (with interrupt function)	XSDCLK	O	SDRAM clock
125	A4	PIOB[12]	I/O	General-purpose port (with interrupt function)	XSDCS_N	O	SDRAM chip select
126	B3	PIOB[13]	I/O	General-purpose port (with interrupt function)	XSDCKE	O	Clock enable (SDRAM)
127	D4	VDD_IO	VDD	I/O power supply	—	—	
128	B2	GND_IO	GND	I/O ground	—	—	

Note: A1, C3, H2, M2, K6, M7, N7, M12, N13, L11, C13, B13, A13, C11, A3, A2 pins of LFBGA packaged version are NC pins. These pins must be left unconnected.

PIN DESCRIPTION

Pin Name	I/O	Description	Primary/ Secondary	Logic
System				
RESET_N	I	Reset input	—	Negative
OSC0	I	Crystal oscillator connection or external clock input. Connect a crystal oscillator (16 MHz to 33 MHz), if used, to OSC0 and OSC1_N.	—	
OSC1_N	O	Crystal oscillator connection. Leave this pin unconnected if using external clock input.	—	
TBE	I	Test pin. Drive at High level.	—	Negative
Debugging support.				
DBGRQ	I	Debugging pin. Normally connect to ground.	—	Positive
DBGACK	O	Debugging pin. Normally leave open.	—	Positive
TCK	I	Debugging pin. Normally connect to ground.	—	—
TMS	I	Debugging pin. Normally drive at High level.	—	Positive
nTRST	I	Debugging pin. Normally connect to ground.	—	Negative
TDI	I	Debugging pin. Normally drive at High level.	—	Positive
TDO	O	Debugging pin. Normally leave open.	—	Positive
General-purpose I/O ports				
PIOA[15:0]	I/O	General-purpose port. Not available for use as port pins when secondary functions are in use.	Primary	Positive
PIOB[15:0]	I/O	General-purpose port. Not available for use as port pins when secondary functions are in use. Note that enabling DRAM controller with MODE[2:0] inputs permanently configures PIOB[15:9] for their secondary functions, making them unavailable for use as port pins.	Primary	Positive

Pin Name	I/O	Description	Primary/ Secondary	Logic
External Bus				
XA[23:19]	O	Address bus to external RAM, external ROM, external I/O banks, and external DRAM. After a reset, these pins are configured for their primary function (PIOA[14:10]).	Secondary	Positive
XA[18:0]	O	Address bus to external RAM, external ROM, external I/O banks, and external DRAM	—	Positive
XD[15:0]	I/O	Data bus to external RAM, external ROM, external I/O banks, and external DRAM	—	Positive
External bus control signals				
XROMCS_N	O	ROM bank chip select	—	Negative
XRAMCS_N	O	SRAM bank chip select	—	Negative
XIOCS_N[0]	O	I/O bank 0 chip select	—	Negative
XIOCS_N[1]	O	I/O bank 1 chip select	—	Negative
XOE_N	O	Output enable/read enable	—	Negative
XWE_N	O	Write enable	—	Negative
XBS_N[1:0]	O	Byte select: XBS_N[1] for MSB; XBS_N[0] for LSB	—	Negative
XBWE_N[0]	O	LSB write enable	—	Negative
XBWE_N[1]	O	MSB write enable	—	Negative
XWR	O	Data transfer direction for external bus, used when connecting to Motorola I/O devices. This represents the secondary function of pin PIOA[15], produced by setting bit 7 in the port control (GPCTL) register to "1."	Secondary	—
XWAIT	I	External I/O bank 0 WAIT signal. This input permits access to devices slower than register settings.	Secondary	Positive
External bus control signals (DRAM)				
XRAS_N	O	Row address strobe. Used for both EDO DRAM and SDRAM.	Secondary	Negative
XCAS_N	O	Column address strobe signal (SDRAM)	Secondary	Negative
XSDCLK	O	SDRAM clock (same frequency as internal system clock)	Secondary	—
XSDCKE	O	Clock enable (SDRAM)	Secondary	—
XSDCS_N	O	Chip select (SDRAM)	Secondary	Negative
XDQM[1]/ XCAS_N[1]	O	Connected to SDRAM: DQM (MSB) Connected to EDO DRAM: column address strobe signal (MSB)	Secondary	Positive/ Negative
XDQM[0]/ XCAS_N[0]	O	Connected to SDRAM: DQM (LSB) Connected to EDO DRAM: column address strobe signal (LSB)	Secondary	Positive/ Negative

Pin Name	I/O	Description	Primary/ Secondary	Logic
DMA control signals				
DREQ0	I	Ch 0 DMA request signal, used when DMA controller configured for DREQ type	Secondary	Positive
DREQCLR0	O	Ch 0 DREQ signal clear request. The DMA device responds to this output by negating DREQ.	Secondary	Positive
TCOUT0	O	Indicates to Ch 0 DMA device that last transfer has started	Secondary	Positive
DREQ1	I	Ch 1 DMA request signal, used when DMA controller configured for DREQ type	Secondary	Positive
DREQCLR1	O	Ch 1 DREQ signal clear request. The DMA device responds to this output by negating DREQ.	Secondary	Positive
TCOUT1	O	Indicates to Ch 1 DMA device that last transfer has started	Secondary	Positive
SIO				
STXD	O	SIO transmit signal	Secondary	Positive
SRXD	I	SIO receive signal	Secondary	Positive
UART				
SIN	I	Serial data input	Secondary	Positive
SOUT	O	Serial data output	Secondary	Positive
CTS	I	Clear To Send. Indicates that modem or data set is ready to transfer data. Bit 4 in modem status register reflects this input.	Secondary	Negative
DSR	I	Data Set Ready. Indicates that modem or data set is ready to establish a communications link with UART. Bit 5 in modem status register reflects this input.	Secondary	Negative
DCD	I	Data Carrier Detect. Indicates that modem or data set has detected data carrier signal. Bit 7 in modem status register reflects this input.	Secondary	Negative
DTR	O	Data Terminal Ready. Indicates that UART is ready to establish a communications link with modem or data set. Bit 0 in modem control register controls this output.	Secondary	Negative
RTS	O	Request To Send. Indicates that UART is ready to transfer data to modem or data set. Bit 1 in modem control register controls this output.	Secondary	Negative
RI	I	Ring Indicator. Indicates that modem or data set has received telephone ring indicator. Bit 6 in modem status register reflects this input.	Secondary	Negative

Pin Name	I/O	Description	Primary/ Secondary	Logic
PWM signals				
PWMOUT0	O	Ch 0 PWM output	Secondary	Positive
PWMOUT1	O	Ch 1 PWM output	Secondary	Positive
Analog-to-digital converter				
AIN[0]	I	Ch 0 analog input	—	
AIN[1]	I	Ch 1 analog input	—	
AIN[2]	I	Ch 2 analog input	—	
AIN[3]	I	Ch 3 analog input	—	
AIN[4]	I	Ch 4 analog input	—	
AIN[5]	I	Ch 5 analog input	—	
AIN[6]	I	Ch 6 analog input	—	
AIN[7]	I	Ch 7 analog input	—	
VREF	I	Analog-to-digital converter convert reference voltage	—	
AVDD		Analog-to-digital converter power supply	—	
AGND		Analog-to-digital converter ground	—	
Interrupt signals				
EXINT3 EXINT2 EXINT1 EXINT0	I	External interrupt input signals	—	Positive/ Negative
EFIQ_N	I	External fast interrupt input signal. Interrupt controller connects this to CPU FIQ input.	—	Negative
MODE				
MODE[2:0]	I	Operating mode control signals	—	
Power supplies				
VDD_CORE	—	Core power supply	—	
VDD_IO	—	I/O power supply	—	
GND_CORE	—	Core ground	—	
GND_IO	—	I/O ground	—	

DESCRIPTION OF FUNCTIONS

CPU

CPU core:	ARM7TDMI
Operating frequency:	1 MHz to 33 MHz
Instructions:	ARM instruction (32-bit length) and Thumb instruction (16-bit length) can be mixed.
General register bank:	31 × 32 bits
Built-in barrel shifter:	ALU and barrel shift operations can be executed by one instruction.
Multiplier:	32 bits × 8 bits (Modified Booth's Algorithm)
Built-in debug function:	JTAG interface, break point register

Built-in Memory

RAM:	8 KB (2K × 32 bits)
	Connected to processor bus (read: 1 cycle access, write: 2 cycle access)

Interrupt Controller

Fast interrupt input (FIQ) and interrupt input (IRQ) are employed as interrupt input signals of ARM core. The interrupt controller controls these interrupt signals going to ARM core.

- (1) Interrupt sources of ML674000
 - FIQ: 1 source, external source (external pin: EFIQ_N)
 - IRQ: 23 sources, internal sources : 19, external sources : 4 (external pins: EXINT[3:0])
- (2) Interrupt priority level
 - Priority can be set in 8 levels for each source.
- (3) External interrupt pin input
 - Level sense: Interrupt signal level is selected.
 - Edge sense: Rise or fall is selected.
- (4) External fast interrupt pin input
 - Edge sense: Fall edge is detected.

Timer

7 channels of 16-bit reload timers are employed. Of these, 1 channel is used as system timer for OS. The timers of other 6 channels are used in application software.

- (1) System timer: 1 channel
 - 16-bit auto reload timer: Used as system timer for OS
(This timer is incorporated in μ PLAT-7B.)
 - Interval mode
- (2) Application timer: 6 channels
 - 16-bit auto reload timer
 - One shot, interval mode
 - Clock can be set for each channel

WDT

This MCU contains a Watch Dog Timer that can also function as an interval timer.

- (1) 16-bit timer
- (2) Watch dog timer or interval timer mode can be selected
- (3) Interrupt or reset generation
 - Watchdog timer mode: generates reset or interrupt when the timer is overflows.
 - Interval timer mode: generates interrupt when the timer reaches an overflow condition.
- (4) Maximum period: 200 msec or longer

PWM

This MCU contains two PWM (Pulse Width Modulation) channels which can change duty cycle within a certain fixed period. The PWM output resolution is 16 bits for each channel.

Serial Interface

This LSI contains two channels of serial interface.

- (1) UART without FIFO: 1 channel
This serial interface is incorporated in μ PLAT-7B.
- (2) UART with 16-byte FIFO: 1 channel
This is ACE (Asynchronous Communication Element) equivalent in function to 16550A. It has 16-byte FIFO in both sending and receiving.

GPIO

This LSI contains two 16-bit parallel ports.

- (1) Input or output can be selected for each bit.
- (2) Interrupt can be used for all 16 bits of each channel, and all GPIO pins can be used as interrupt inputs.
- (3) Interrupt mask and interrupt mode (level) can be set for all bits.
- (4) Configured as inputs immediately after reset.

AD Converter

This is a successive approximation type AD converter.

- (1) 10 bits \times 8 channels
- (2) Sample and hold function
- (3) Scan mode and select mode are supported
- (4) Interrupt is generated after completion of conversion.
- (5) Minimum conversion time of 5 μ s.

DMAC

This MCU contains a two channel direct memory access controller which transfers data between memory and memory, between I/O and memory and between I/O and I/O.

- (1) Number of channels: 2 channels
- (2) Channel priority level: Fixed mode
Channel priority level is always fixed (channel 0 > 1).
Roundrobin
Priority level of the channel requested for transfer is kept lowest.
- (3) Maximum number of transfers: 65,536 times (64K times)
- (4) Data transfer size: Byte (8 bits), half-word (16 bits), word (32 bits)
- (5) Bus request system: Cycle steal mode
Bus request signal is asserted for each DMA transfer cycle.
Burst mode
Bus request signal is asserted until all transfers of transfer cycles are complete.
- (6) DMA transfer request: Software request
By setting the software transfer request bit inside DMAC, the CPU starts DMA transfer.
External request
DMA transfer is started by external request allocated to each channel.
- (7) Interrupt request: Interrupt request is generated in CPU after the end of DMA transfers for the set number of transfer cycles or after occurrence of error.
Interrupt request signal is output separately for each channel.
Interrupt request signal output can be masked for each channel.

External Memory Controller

Controls access of externally connected devices such as ROM (FLASH), SRAM, SDRAM (EDO DRAM) and IO devices.

- (1) ROM (FLASH) access function
 - Supports 16-bit device
 - Supports FLASH memory: Byte write (can be written only by IF equivalent to SRAM).
 - Access timing setting
- (2) SRAM access function
 - Supports 16-bit device
 - Supports asynchronous SRAM
 - Access timing setting
- (3) DRAM access function
 - Supports 16-bit device
 - Supports EDO/SDRAM: Simultaneous connections to EDO-DRAM and SDRAM cannot be made.
 - Access timing setting
- (4) External IO access function
 - Supports 8-bit/16-bit device
 - Supports 2 banks independently
 - Supports external wait input: XWAIT (IO bank 0 only)
 - Access timing setting (for each bank)

Power Management

HALT and STANDBY functions are supported as power save functions.

- (1) HALT mode
 - HALT object
 - CPU, internal RAM, AHB bus control
 - HALT mode setting: Set by the system control register.
 - HALT mode cancelling: Reset, interrupt
- (2) STANDBY mode
 - Stops the clock of entire LSI.
 - STANDBY mode setting: Specified by the system control register.
 - STANDBY mode cancelling: Reset, external interrupt (other than FIQ)

ABSOLUTE MAXIMUM RATINGS

Item	Symbol	Conditions	Rating	Unit
Digital power supply voltage (core)	V_{DD_CORE}	GND = AGND = 0 V Ta = 25°C	-0.3 to +3.6	V
Digital power supply voltage (I/O)	V_{DD_IO}		-0.3 to +4.6	
Input voltage	V_I		-0.3 to $V_{DD_IO}+0.3$	
Output voltage	V_O		-0.3 to $V_{DD_IO}+0.3$	
Analog power supply voltage	AV_{DD}		-0.3 to $V_{DD_IO}+0.3$	
Analog reference voltage	V_{REF}		-0.3 to $V_{DD_IO}+0.3$ and -0.3 to $AV_{DD} +0.3$	
Analog input voltage	V_{AI}		-0.3 to V_{REF}	mA
Input current	I_I		-10 to +10	
High level output current	I_{OH}		+10	
Low level output current *1	I_{OL}		-20	
Low level output current *2		-30		
Power dissipation	P_D	Ta = 85°C per package	530	mW
Storage temperature	T_{STG}	—	-50 to +150	°C

Notes

1. All output pins except XA[15:0]
2. XA[15:0]

RECOMMENDED OPERATING CONDITIONS

(GND = 0 V)

Item	Symbol	Conditions	Minimum	Typical	Maximum	Unit
Digital power supply voltage (core)	V_{DD_CORE}	$V_{DD_IO} \geq V_{DD_CORE}$	2.25	2.5	2.75	V
Digital power supply voltage (I/O)	V_{DD_IO}		3.0	3.3	3.6	
Analog power supply voltage	AV_{DD}	$AV_{DD} = V_{DD_IO}$	3.0	3.3	3.6	
Analog reference voltage	V_{REF}	$V_{REF} = AV_{DD} = V_{DD_IO}$	3.0	3.3	3.6	
Storage hold voltage	V_{DDH}	$f_{OSC} = 0$ Hz	2.25	—	3.6	
Operating frequency	f_{OSC}	$V_{DD_CORE} = 2.25$ to 2.75 $V_{DD_IO} = 3.0$ to 3.6 *	1	—	33.333	MHz
Ambient temperature	Ta	—	-40	25	+85	°C

Note

Oscillator frequencies between 16 MHz and 33 MHz. Minimum of 2.56 MHz for external SDRAM. Minimum of 6.4 MHz for external EDO DRAM. Minimum of 2 MHz for analog-to-digital converter.

ELECTRICAL CHARACTERISTICS

DC Characteristics

($V_{DD_CORE} = 2.25$ to 2.75 V, $V_{DD_IO} = 3.0$ to 3.6 V, $T_a = -40$ to $+85^\circ\text{C}$)





Item	Symbol	Conditions	Minimum	Typical	Maximum	Unit	
High level input voltage	V_{IH}	—	2.0	—	$V_{DD_IO}+0.3$	V	
Low level input voltage	V_{IL}		-0.3	—	0.8		
Schmitt input buffer threshold voltage	V_{T+}		—	—	1.6		2.1
	V_{T-}		0.7	—	1.1		—
	V_{HYS}		0.4	—	0.5		—
High level output voltage	V_{OH}	$I_{OH} = -100 \mu\text{A}$	$V_{DD}-0.2$	—	—	—	
		$I_{OH} = -4 \text{ mA}$	2.4	—	—		
Low level output voltage	V_{OL}	$I_{OL} = 100 \mu\text{A}$	—	—	0.2	—	
Low level output voltage * ¹		$I_{OL} = 4 \text{ mA}$	—	—	0.4		
Low level output voltage * ²		$I_{OL} = 6 \text{ mA}$	—	—	0.4		
Input leak current * ³	I_{IH}/I_{IL}	$V_I = 0 \text{ V}/V_{DD_IO}$	-10	—	10	μA	
Input leak current * ⁴		$V_I = 0 \text{ V}$ Pull-up resistance of 50 k Ω	10	66	200		
Output leak current	I_{LO}	$V_O = 0 \text{ V}/V_{DD_IO}$	-10	—	10	—	
Input pin capacitance	C_I	—	—	6	—	pF	
Output pin capacitance	C_O	—	—	9	—		
I/O pin capacitance	C_{IO}	—	—	10	—		
Analog reference power supply current	I_{REF}	Analog-to-digital converter operative * ⁵	—	320	650	μA	
		Analog-to-digital converter stopped	—	1	2		
Current consumption (STANDBY)	I_{DD_CORE}	$T_a = 25^\circ\text{C}$ * ⁶	—	3	45	μA	
	I_{DD_IO}		—	1	5		
Current consumption (HALT) * ⁷	I_{DDH_CORE}	$f_{OSC} = 16 \text{ MHz}$ $C_L = 50 \text{ pF}$	—	8	15	mA	
	I_{DDH_IO}		—	2	5		
Current consumption (RUN)	I_{DD_CORE}		—	15	25	mA	
	I_{DD_IO}		—	18	30		

Notes

1. All output pins except XA[15:0]
2. XA[15:0]
3. All input pins except RESET_N
4. RESET_N pin, with 50 k Ω pull-up resistance
5. Analog-Digital Converter operation ratio is 20%
6. V_{DD_IO} or 0 V for input ports; no load for other pins
7. DRAM function stop by MODE pin setting

Power Consumption

The values in the following charts are measured values in the operating conditions indicated. The samples were taken during normal operation in ARM mode with all peripheral clocks activated. Instructions were being executed from external memory.



Analog-to-Digital Converter Characteristics $(V_{DD_CORE} = 2.50\text{ V}, V_{DD_IO} = 3.3\text{ V}, T_a = 25^\circ\text{C})$

Item	Symbol	Conditions	Minimum	Typical	Maximum	Unit
Resolution	n	—	—	—	10	bit
Linearity error	E_L	Analog input source impedance $R_i \leq 1\text{ k}\Omega$	—	± 3	—	LSB
Differential linearity error	E_D		—	± 3	—	
Zero scale error	E_{ZS}		—	± 3	—	
Full scale error	E_{FS}		—	± 3	—	
Conversion time	t_{CONV}	—	5	—	—	μs
Throughput		—	10	—	200	kHz


Note: V_{DD_IO} and AV_{DD} should be supplied separately.


- Definition of Terms

- (1) Resolution: Minimum input analog value recognized. For 10-bit resolution, this is $(V_{REF} - A_{ground}) \div 1024$.
- (2) Linearity error: Difference between the theoretical and actual conversion characteristics. (Note that it does not include quantization error.) The theoretical conversion characteristic divides the voltage range between V_{REF} and $AGND$ into 1024 equal steps.
- (3) Differential linearity error: Difference between the theoretical and actual input voltage change producing a 1-bit change in the digital output anywhere within the conversion range. This is an indicator of conversion characteristic smoothness. The theoretical value is $(V_{REF} - A_{ground}) \div 1024$.
- (4) Zero scale error: Difference between the theoretical and actual conversion characteristics at the point where the digital output switches from “0x000” to “0x001.”
- (5) Full scale error: Difference between the theoretical and actual conversion characteristics at the point where the digital output switches from “0x3FE” to “0x3FF.”

PACKAGE DIMENSIONS

(Unit : mm)





Notes for Mounting the Surface Mount Type Package

The surface mount type packages are very susceptible to heat in reflow mounting and humidity absorbed in storage.

Therefore, before you perform reflow mounting, contact Oki's responsible sales person for the product name, package name, pin number, package code and desired mounting conditions (reflow method, temperature and times).

REVISION HISTORY

Document No.	Date	Page		Description
		Previous Edition	Current Edition	
PEDL674000-01	Oct., 2001	–	–	Preliminary edition 1
PEDL674000-02	May 17, 2002	–	–	Preliminary edition 2
		1	1	Feature Table rewritten.
		2-13	2-12	Pin names are changed.
		14-16	13-15	Description rewritten.
		17	16-37	Electrical characteristics added.
FEDL674000-01	Aug. 8, 2002	–	–	Final edition 1
		1	1	Number of interrupt sources corrected.
		8	8	TBE signal description corrected.
		8	8	Pin numbers of XA[23:19] and XA[18:0] corrected.
		15-36	15-50	Description rewritten.
FEDL674000-02	Dec. 10, 2002	–	–	Final edition 2
		1	1 to 2	Description changed. Supported DRAM area changed from 16Mbytes to 64Mbytes. Add 144-pin LFBGA package.
		–	5	Add Pin layout for LFBGA package.
		4 to 7	6 to 9	Change table of pin list. (Add LFBGA description and correct some misdescription.)
		8 to 11	10 to 13	Change table of pin description. (Correct some misdescription.)
		12 to 14	14 to 16	Description changed.
		18 to 50	–	Description of AC characteristics Deleted. Please refer to User's Manual.
		51	21	The values of Zero scale error and Full scale error of Analog-to-Digital converter are corrected.
		–	23	Add Package Dimensions for LFBGA package.

NOTICE

1. The information contained herein can change without notice owing to product and/or technical improvements. Before using the product, please make sure that the information being referred to is up-to-date.
2. The outline of action and examples for application circuits described herein have been chosen as an explanation for the standard action and performance of the product. When planning to use the product, please ensure that the external conditions are reflected in the actual circuit, assembly, and program designs.
3. When designing your product, please use our product below the specified maximum ratings and within the specified operating ranges including, but not limited to, operating voltage, power dissipation, and operating temperature.
4. Oki assumes no responsibility or liability whatsoever for any failure or unusual or unexpected operation resulting from misuse, neglect, improper installation, repair, alteration or accident, improper handling, or unusual physical or electrical stress including, but not limited to, exposure to parameters beyond the specified maximum ratings or operation outside the specified operating range.
5. Neither indemnity against nor license of a third party's industrial and intellectual property right, etc. is granted by us in connection with the use of the product and/or the information and drawings contained herein. No responsibility is assumed by us for any infringement of a third party's right which may result from the use thereof.
6. The products listed in this document are intended for use in general electronics equipment for commercial applications (e.g., office automation, communication equipment, measurement equipment, consumer electronics, etc.). These products are not, unless specifically authorized by Oki, authorized for use in any system or application that requires special or enhanced quality and reliability characteristics nor in any system or application where the failure of such system or application may result in the loss or damage of property, or death or injury to humans.
Such applications include, but are not limited to, traffic and automotive equipment, safety devices, aerospace equipment, nuclear power control, medical equipment, and life-support systems.
7. Certain products in this document may need government approval before they can be exported to particular countries. The purchaser assumes the responsibility of determining the legality of export of these products and will take appropriate and necessary steps at their own expense for these.
8. No part of the contents contained herein may be reprinted or reproduced without our prior permission.

Copyright 2002 Oki Electric Industry Co., Ltd.