



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089
<http://www.nteinc.com>

NTE3144 thru NTE3147 Light Emitting Diode – 5mm

Features:

- All Plastic Mold Type w/Water Clear Lens:
 - NTE3144 (High Efficiency Red, AlGaP/GaAs)
 - NTE3145 (Yellow Green, GaInN/GaN)
 - NTE3146 (Yellow, AlInGaP/GaAs)
 - NTE3147 (Orange, AlInGaP/GaAs)

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Power Dissipation, P_D		
NTE3144, NTE3146, NTE3147	90mW
NTE3145	84mW
Continuous Forward Current, I_F		
NTE3144, NTE3147	30mA
NTE3145, NTE3146	25mA
Peak Forward Current (0.1 ms pulse width, 1/10 duty cycle), I_{FM}	50mA
Reverse Voltage, V_R	5V
LED Junction Temperature, T_j	+100°C
Operating Temperature Range, T_{opr}	-25° to +85°C
Storage Temperature Range, T_{stg}	-40° to +100°C
Lead Temperature (During Soldering, 5sec max, 1.6mm below package base)	260°C

Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit	
View Angle of Half Power	2θ1/2	$I_F = 20\text{mA}$	-	30	-	Degree	
Forward Voltage	V_F	$I_F = 20\text{mA}$	-	NTE3144, NTE3147	2.05	2.80	V
NTE3145				2.15	2.80	V	
NTE3146				2.10	2.80	V	
Reverse Current	I_R	$V_R = 5\text{V}$	-	-	10	uA	
Luminous Intensity	I_V	$I_F = 20\text{mA}$, Note 1	40	NTE3144, NTE3147	60	-	mcd
NTE3145				80	-	mcd	
NTE3146				35	50	-	mcd

Note 1. Tolerance: 30%, measured using Exeltron 2001.

Electrical Characteristics (Cont'd): ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Peak Emission Wavelength NTE3144, NTE3147	λ_p	$I_F = 20\text{mA}$	-	625	-	nm
NTE3145			-	570	-	nm
NTE3146			-	589	-	nm
Dominate Wave Length NTE3144, NTE3147	$\lambda_d(\text{HUE})$	$I_F = 20\text{mA}$, Note 2	-	618	-	nm
NTE3145			-	567	-	nm
NTE3146			-	585	-	nm
Spectrum Width of Half Valve NTE3144, NTE3147	$\Delta\lambda$	$I_F = 20\text{mA}$	-	45	-	nm
NTE3145			-	30	-	nm
NTE3146			-	35	-	nm
Terminal Capacitance NTE3144, NTE3147	C_t	$V = 0\text{V}$, $F = 1\text{MHz}$	-	6	-	pF
NTE3145, NTE3146			-	7	-	pF
Response Frequency	F_C		-	4	-	MHz

Note 2. The dominate wavelength, λ_d , is derived from the CIE Chromaticity Diagram and represents the color of the device.

